





G4-FLX SERIES RECORDING UPON MOTION QUICK GUIDE

Motion Configuration

Motion Settings

1. Hook up your G4-FLX device to your display monitor and login to your administrator account.
2. Select the “Menu option”  and then select “Settings”.  Settings
3. Navigate to the Camera settings and select “**Motion**”.



4. Within this section you will find multiple motion settings to configure. These settings include the following: **Motion**, **Sensitivity**, **Duration** and **Area**. Please review the following page for more details on each setting’s purpose.

Motion – Here you can enable or disable motion for the channel setting up.

Duration – Here you can set the time frame the unit will delay between motion events.

The screenshot shows the 'Motion Settings' page. On the left, there's a sidebar with 'Manage Camera', 'Image', 'Motion' (selected), and 'PTZ'. The main area has a camera preview with a green grid overlay. Below the preview are controls for 'Camera' (TD-9541E2), 'Motion' (ON), a sensitivity slider (set to 8), and a duration dropdown (5 Secs). On the right, a table lists camera settings:


Camera Name	Motion	Sensitivity	Duration
TD-9541E2	ON	8	5 Secs
TD-9432S1	ON	8	5 Secs
	OFF		

Annotations include:

- A box pointing to the green grid in the preview: "Above is where you can region off or add areas within the FOV to trigger motion. When highlighted with green boxes, the areas selected will pick up motion. When not highlighted, motion will not be triggered within that area."
- A box pointing to the 'Motion' dropdown in the table: "Motion – Here you can enable or disable motion for the channel setting up."
- A box pointing to the 'Sensitivity' column in the table: "Sensitivity – Here you can adjust how sensitive motion is picked up. The higher the sensitivity is set the more sensitive motion is picked up and vice versa."
- A box pointing to the 'Duration' column in the table: "Duration – Here you can set the time frame the unit will delay between motion events."
- A box pointing to the 'Apply' button at the bottom right: "Once all settings are set as needed select **Apply** to save."

Record Setup

1. Select the "Menu option"  and then select "Settings".



2. Navigate to the Record settings and select "Record Schedule".

The screenshot shows the main menu with several categories:

- Camera**: Add Camera | Edit Camera | Image Settings | Motion | PTZ
- Record**: Encode Parameters | **Record Schedule** | Advanced
- Alarm**: Sensor Alarm | Alarm-out | Motion Alarm
- Disk**: Disk Management | Storage Mode | Disk
- Network**: TCP/IPv4 | DDNS | Port | E-mail | Network Status
- Account and Authority**: Add User | Edit User | Edit Permission Group | Modify Password
- System**: Basic | Date and Time | Information | View Log | Backup and Restore

The 'Record Schedule' option under the 'Record' category is highlighted with a white box and an arrow.

3. Select the circle next to **"Motion Record"** and then select **"Apply"** to save.

The screenshot displays a web interface for configuring recording settings. On the left is a sidebar with a teal header 'Record' containing a sub-menu 'Mode Settings | Advanced'. Below this are sections for 'Encode Parameters', 'Stream Settings', 'Record Schedule', and 'Record Status'. The main content area is titled 'Mode Settings' and 'Advanced'. It features a 'Record Mode' section with a 'Mode' dropdown set to 'Auto'. Below this, a list of radio button options is shown: 'Motion Record' (selected and highlighted with a white box), 'Sensor Record', 'Motion Record+Sensor Record', 'Always(24x7) Record+Motion Record', 'Always(24x7) Record+Sensor Record', and 'Always(24x7) Record+Motion Record+Sensor Record'. An arrow points from the 'Motion Record' text to its selected radio button. Further down is a 'Manual Record Settings' section with a 'Record Time' dropdown set to 'Manual'. At the bottom right is an 'Apply' button.

Record >
Mode Settings | Advanced

Encode Parameters
Event Recording Settings |
Schedule Recording Settings

Stream Settings
Sub Stream Settings

Record Schedule
Schedule Config
Edit Schedules

Record Status
View Record Status

Mode Settings Advanced

Record Mode

Mode Auto

☒ Motion Record

☐ Sensor Record

☐ Motion Record+Sensor Record

☐ Always(24x7) Record+Motion Record

☐ Always(24x7) Record+Sensor Record

☐ Always(24x7) Record+Motion Record+Sensor Record

Manual Record Settings

Record Time Manual

Apply