

UNIVIEW RECORDING ON MOTION SETUP GUIDE

First step in setting up your Uniview NVR to record on motion is to schedule the recording. To do so go to **Menu->Storage->Recording-> Check in Enable Schedule**, and then click Apply.



Next, click **Edit** on the right side of the menu. In the Edit Schedule menu, select "**Motion**" from the drop down box.

		D1				Camera	(Snanshot
		Edit Schedule							
•	•		day	Monc				Select Day	Advanc
-	-	Type Normal		Ту			All Day		
Edit		Normal	^ Type	0.0	24 .		0.0		ocate
Norm		Motion	^ Type	00	00 :	Ψ 	00	00 .	ocurt
Event		M and A	^ Type	00	00 -	*	0.0	00 .	
* Motio	*	M or A	Type	0.0	00 -	*	00	00 .	
-	*	Normal	1 Туре	0.0	00 :	*	0.0	00 :	
- Alarm	*	Normal	1 Type	0.0	00 -	^	0.0	00 .	
🛫 📃 M and	*	Normal	_ Туре	00	00 :	<u>^</u>	0.0	00 :	
- Mor/	-	Normal	_ Туре	00	00 :	ĉ	00	00 :	
None None	Sat Sun Holiday	Wed Thu Fri	Tue	on C	⊘ Mo	Ali		Сору То	



Next you will select the days you wish to record on motion. In this setup we will select "**All**". If certain days do not apply in your setup, be sure to leave them unchecked. Once all days needed to record on motion are chosen, select OK.

-		6						
Snapshot		Cam	era		D1			
Advanc					Edit Sch	nedule		
Auvanc	Select Day			Monday			•	
lard D	All Day		-		Туре	Motion	•	
llocate		00	► 24 ·	00	Туре	Motion	*	Ed
	00 :	00	00 :	00	Туре	Normal		Norn
	00 :	00	00 :	00	Туре	Normal	*	Event
	00 :	00	: 00 :	00	Туре	Normal	· ·	Moti-
	00 :	00	: 00 :	00	Туре	Normal	*	Alarr
	00 :	00	: 00 :	00	Туре	Normal	*	
	00 :	00	00 :	00	Туре	Normal	*	M an
	00 :	00	: 00 :	00	Туре	Normal	Ψ.	M or
	Сору То	X		on 🗹 T	ue 🗹 Wed	☑ Thu ☑ Fri ☑ Sat ☑ Sun	 Holiday 	None
		'n	2				12-1	
						OK Cancel		
		1						

Next you will select Copy and choose all of the channels you wish to record on motion. Once chosen select Ok and finally hit Apply.





Finally you will setup your motion settings. To do so go to **Menu->Alarm->Motion**. Click the check box to enable motion for your selected channel, then select "**Trigger actions**" (reference second image). Within trigger actions under the Recording tab you will check box the matching channel number you are setting up. These two tasks need to be accomplished one at a time on each channel. Once completed select "**Apply**" to save. You are now setup to record on motion. (If you'd like more in depth information in regards to Trigger actions and your other motion options, please review your NVR manual)



			_	_	N	lenu	_	_	_	_	_	_
	Input/Output	Moti	on Detection	n -								
Backup					Trigge	r Actions					_	
	Buzzer											
	Send Email											
Manual	Recording P	reset Pr	eview Ala	rm Output	Snapshot							
System	All	✓ D1	D2	D3	D4	D5	D6	D7	D8			
						0015			DIU			_
Storage												
Alarm												
Maintain							div.	OK		Cancol		
Shutdown						6		UK		cancer		
A. 2000 AS										Apply	В	ack